

| | | |
|-----------------------|---------|-----------------------|
| <input type="radio"/> | 8000ohm | <input type="radio"/> |
| <input type="radio"/> | 6600ohm | <input type="radio"/> |
| <input type="radio"/> | CT | <input type="radio"/> |
| <input type="radio"/> | 6600ohm | <input type="radio"/> |
| <input type="radio"/> | 8000ohm | <input type="radio"/> |

impedance primary: 8Kohm / 6K6ohm
inductance primary 8Kohm: => 660 Henry (@240V,50Hz open circuit)
inductance primary 6K6ohm: => 540 Henry (@240V,50Hz open circuit)
impedance secondary: 4, 8, 16ohm
max power: 70W
minimum reproducible frequency at max power (70W): 20Hz/-3dB
Re (a-a) 8Kohm, 185ohm +/-5%
Re (a-a) 6K6ohm, 165ohm +/-5%